

Filter by interface

1. Match by incoming interface

Match: **-i** incoming_interface

Available for: INPUT, FORWARD and PREROUTING chains.

Example: `iptables -A INPUT -i wlan0 -j ACCEPT`

2. Match by outgoing interface

Match: **-o** outgoing_interface

Available for: FORWARD, OUTPUT and POSTROUTING chains.

Example: `iptables -A OUTPUT -o enp8s0 ACCEPT`

Note: It's good practice to permit traffic on the loopback interface (**lo**)